

## Hegel P20, P30 RC-5 code table

V2

09.09.2020

System 16 (Preamp 1)																																		
Function	Command	Description	HEX-Long																															
<b>BAL1</b>	1	Source select	0000	0073	0000	000C	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0CA4				
<b>BAL2</b>	8	Source select	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0020	0020	0CC5			
<b>CD</b>	3	Source select	0000	0073	0000	000C	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0CA4			
<b>VIDEO</b>	2	Source select	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0CC5				
<b>AUX</b>	6	Source select	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0040	0CC5			
<b>HT</b>	7	Source select	0000	0073	0000	000C	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0CA4			
<b>Mute</b>	13	Mute toggle	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0040	0020	0CA4		
	13 (alt)	Mute toggle (alt)	0000	0073	0000	000C	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0040	0020	0CA4		
<b>Volume Up</b>	16	Volume control	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0020	0020	0020	0020	0CC5		
	16 (alt)	Volume control (alt)	0000	0073	0000	000C	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0020	0020	0020	0020	0CC5	
<b>Volume Down</b>	17	Volume control	0000	0073	0000	000B	0020	0020	0040	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0020	0020	0020	0040	0020	0CA4	
	17 (alt)	Volume control (alt)	0000	0073	0000	000C	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0040	0020	0020	0020	0020	0040	0020	0CA4
<b>IN +</b>	64	Source select	0000	0073	0000	000C	0040	0020	0020	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0CC5	
	64 (alt)	Source select (alt)	0000	0073	0000	000C	0040	0040	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0CC5	
<b>IN -</b>	70	Source select	0000	0073	0000	000B	0040	0020	0020	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0040	0020	0CC5		
	70 (alt)	Source select (alt)	0000	0073	0000	000B	0040	0040	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0040	0020	0CC5		
<b>ECO (P30 only)</b>	79	Low Power Toggle	0000	0073	0000	000C	0040	0020	0020	0040	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0020	0020	0020	0CA4	
	79 (alt)	Low Power Toggle (alt)	0000	0073	0000	000C	0040	0040	0020	0020	0040	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0020	0040	0020	0020	0020	0020	0020	0020	0CA4	

Important note

All commands meant to be used repeatedly must be programmed with two separate HEX codes to work as intended.  
 Program your remote so that using the command multiple times in a row alternates between the original and the alternate HEX codes.

Explanation:  
 1<sup>st</sup> use of the command: Use the original HEX code  
 2<sup>nd</sup> use of the command: Use the alternate (alt) HEX code  
 3<sup>rd</sup> use of the command: Use the original HEX code again

By alternating between the two HEX codes in this manner your Hegel device will register each command individually.  
 This will prevent the command from freezing.